

Title	Ultrasonically powered and controlled microsystem for dual-wavelength optogenetics with a multiload regulation scheme
Authors	Rashidi, Amin;Zamani, Milad;Mondal, Tanmay;Hosseini, Seyedsina;Laursen, Kjeld;Corbett, Brian;Moradi, Farshad
Publication date	2023-01-25
Original Citation	Rashidi, A., Zamani, M., Mondal, T., Hosseini, S., Laursen, K., Corbett, B. and Moradi, F. (2023) 'Ultrasonically powered and controlled microsystem for dual-wavelength optogenetics with a multiload regulation scheme', IEEE Solid-State Circuits Letters, 6, pp.33-36. https://doi.org/10.1109/LSSC.2023.3239601
Type of publication	Article (peer-reviewed)
Link to publisher's version	10.1109/LSSC.2023.3239601
Rights	© 2023, IEEE. Personal use of this material is permitted. Permission from IEEE must be obtained for all other uses, in any current or future media, including reprinting/republishing this material for advertising or promotional purposes, creating new collective works, for resale or redistribution to servers or lists, or reuse of any copyrighted component of this work in other works.
Download date	2026-09-20 14:25:45
Item downloaded from	https://hdl.handle.net/10468/16913



UCC

University College Cork, Ireland
Coláiste na hOllscoile Corcaigh

Ultrasonically Powered and Controlled Microsystem for Dual-Wavelength Optogenetics with a Multi-Load Regulation Scheme

Amin Rashidi, *Member, IEEE*, Milad Zamani, *Member, IEEE*, Tanmay Mondal, Seyedsina Hosseini, Kjeld Laursen, Brian Corbet, and Farshad Moradi, *Senior Member, IEEE*

Abstract—This paper presents an ultrasonically powered dual-wavelength optogenetic device that targets simultaneous excitation and inhibition of neural activities, or in a broader sense, optical stimulation in two distinct wavelengths for targeting different populations of neurons. This can be applied to a variety of neurological disorders. The device features a load regulator circuit that shares the available power budget between two μ LEDs in a power-efficient and controlled way suppressing the need for adaptive matching and overvoltage protection circuits. Furthermore, the regulator circuit is capable of detecting power burst availability on the device and generating a control signal, accordingly. For 5.25mW acoustic power at the device's surface, the rectified voltage, and the total current load of the system are regulated to 2.79 V and 600 μ A, respectively. The maximum chip and device efficiencies of 92.5 % and 31.8 % are measured, respectively. The total die area in 180 nm CMOS technology nose and the estimated system volume are 0.16 mm² and 0.572 mm³, respectively.

Index Terms—Aperture efficiency, dual-wavelength optogenetics, dust, load regulator, piezoelectric, Ultrasonic power transfer.

I. INTRODUCTION

The emerging technology for ultrasonically powered implantable devices (i.e. neural dusts) has broadened to a vast variety of applications with variable electrical loads from few microwatts (e.g. neural recording [1]–[3], temperature sensing [4], pressure sensing [5], etc.) to several milliwatts (Electrical stimulation [6], Optogenetics [7], [8], etc.). This wide range of applications leads to a highly variable electrical load for multi-functional dusts. However, variable load opens up new challenges. A constant/no matching circuit can result in degradation of aperture efficiency. Furthermore, small loads can lead to overvoltage conditions that can damage active circuits. The former has been addressed in [9] with an adaptive matching circuit at the cost of higher complexity, and uplink communication for tuning the carrier frequency. The latter is

This work was supported by the project STARDUST, which received funding from the European Union's Horizon 2020 research and innovation program under grant agreement No 767092.

Amin Rashidi is with the Faculty of Electrical Engineering, Mathematics, and Computer Science, the Delft University of Technology, the Netherlands.

Milad Zamani, Kjeld Laursen, and Farshad Moradi are with the Department of Electrical and Computer Engineering, Aarhus University, Denmark (E-mail: {mzamani@ece.au.dk}).

Seyedsina Hosseini is with Department of Health Technology Magnetic Resonance, Technical University of Denmark, Denmark.

Tanmay Mondal and Brian Corbet are with Tyndall National Institute, Ireland.




Fig. 1: Architecture of dual-wavelength optogenetic and its timing diagram

addressed in [10] by an overvoltage regulator. In this paper, we address both of the aforementioned challenges using a novel circuit for regulating the total electrical load of the dust by adapting the driving current that goes through a μ LED for biomedical applications (e.g. optogenetics, light-driven drug delivery or photodynamic therapy) according to other variable sources. Furthermore, the proposed circuit offers more advantages at no- or low-extra cost including the longevity management of the energy stored at the dust, demodulation of time-encoded downlink data, weighted control of two loads using one set of data, and overvoltage protection. The proposed system targets the new BIPOLES tandem [11], which can be used for excitation and inhibition of the neurons at the same time. However, this can be applied to other applications within optogenetics, photodynamic therapy, and so on, where there is a dominant load. In the next section, the system architecture and the circuit designs are explained. Section III is devoted to the system integration and the measurement results and the last Section concludes the paper.

II. STRUCTURE AND CIRCUIT DESIGN

Fig. 1 illustrates the system-level architecture for the dual-wavelength optogenetic with the possibility of adding neural




Fig. 2: Proposed Load Regulator schematic.




Fig. 3: The schematic of time-to-digital converter and its timing diagram

recording and backscattering circuits as other variable loads. The system includes a piezoelectric receiver, two μ LEDs for dual-wavelengths optogenetics, an off-chip storage capacitor (C_{Store}), and a die for harvesting power and driving the μ LEDs efficiently in a controlled weighted manner. The die includes DC supply rail generator (including an active rectifier and a double-pass regulator), reference generator, and Power On Reset (POR) circuits adopted from [7]. Furthermore, the die features a novel load regulator driving a blue LED ($LED1$), and a controller followed by a current Digital-to-Analog Converter (DAC) that drives the red LED ($LED2$) according to downlink data. The proposed load regulator is designed to adapt $LED1$ current (I_{LED1}) according to other current loads (I_{LED2} and I_{LV}) to regulate the total current load ($I_{Total} = I_{LED1} + I_{LED2} + I_{LV}$) to the desired value (e.g. which the simple matching circuit is designed for).

An external device generates a series of Ultrasonic Power Bursts (UPBs) to drive the implant, and to send the optogenetic intensity data. As it is shown in the timing diagram of Fig. 1, the load regulator drives $LED1$ only upon the availability of the UPB. This helps in extending the longevity of the energy




Fig. 4: The schematic of the current DAC block.

stored at the 100-nF C_{Stor} to be used by continuous low-power applications like neural recording circuits. However, $LED2$ is driven by the downlink command, embedded in the duration of predefined notches (T1 and T2) in the UPB.

The schematic of the load regulator is shown in Fig. 2. After receiving the POR signal (triggered when V_{Rec} rise above 2.2V [7]), $M2$ senses the rectified voltage (V_{Rec}) as its source and gate are connected to V_{Rec} and V_{Ref} (1.46 V), respectively, and converts the voltage difference into current (voltage to current converter). As long as V_{Rec} is smaller than the target regulated voltage level (2.8V), the drain current of $M2$ (I_{D2}) is smaller than I_{Ref1} , the voltage level at the gate of $M1$ (node X) is pulled down, and $M1$ is in cut-off region. Upon receiving the UPB, as V_{Rec} is charged through the active rectifier and goes above the target regulated voltage, I_{D2} becomes dominant, the voltage level at node X (V_X) increases, and eventually, $M1$ turns on. However, increasing the current load, driven by $M1$ (I_{LED1}) results in a drop on the harvested DC voltage level and consequently I_{D2} . Thus, through a negative loop, the voltage level of V_{Rec} gets regulated. It happens for a certain I_{total} and available ultrasonic power at the dust. All in all, for a certain available power, $M1$ drives the $LED1$ with current level of $I_{LED1} = I_{Total} - I_{LED2} - I_{LV}$. Therefore, by setting I_{LED2} through downlink data, the proposed circuit divides the power/current budget between the two μ LEDs in a power-efficient weighted manner while the total electrical load of the harvester stays constant. Since in the absence of UPB, V_X is pulled down by I_{Ref1} , a Schmitt trigger followed by a digital buffer digitizes V_X , and shares it with other blocks as Burst Availability (BA) signal. Finally, in the absence of UPB (i.e., when $M1$ turns off), I_{Ref2} becomes parallel to I_{Ref1} for adding hysteresis to the circuit functionality and preventing undesirable ringings. The on-chip capacitor $C0$ is for ripple reduction at node X.

The schematic and the timing diagram of the controller block are depicted in Fig. 3. The circuit is mainly a Time-to-Digital Converter (TDC), which is designed to control I_{LED2} . When the BA signal goes to zero (i.e. UPB absence), SWt closes a path, thereby the capacitor C_t is charged with a slope of $dv/dt = I_{Ref,t}/C_t$, where $I_{Ref,t}$ is a reference current. Then, a comparator followed by a rising ED circuit detects the time that voltage at node Y crosses the reference voltage, V_{Ref0} . An 80-ns pulse generated by the ED circuit at the node CLK triggers a 3-bit counter resets the charge over C_t , and disables the comparator (to avoid a transition at its outputs as




Fig. 5: Die photo of the dual-wavelength optogenetic system.




Fig. 6: Experimental setup for the transient measurement.

C_t discharges). Thus, the counter counts the number of CLK happening at time intervals of $t_{LSB} = \frac{C_t}{I_{Ref,t}}(V_{LDO} - V_{Ref0})$. Another ED circuit resets the counter on the onset of each notch. The counter releases the number, $D(0..2)$, when the notch ends and UPB is available again. During the notch, $D(0..2)$ are set to zero as the Output Enable (OE) of the counter is pulled down. If the counter counts more than 7, the counter sets its Overflow (OF) output which keeps C_t in the reset state until the next notch, when the counter gets reset. Thus, during inter-burst delays, $LED2$ is off.

Fig. 4 illustrates the schematic diagram of the employed Current DAC. The DAC utilizes an Opamp in negative feedback to set the drain voltage of the transistors MD0-MD2 to $V_B = 100\text{ mV}$. Thus, MD0-MD2 operate in the triode or cut-off region depending on the digital input. The drain current of MD0 in triode mode I_{D0} is equal to V_B/R_{ON1} . The DAC generates $1-7 \times I_{D0}$ by binary-weighted control of MD0-MD2 according to the downlink data. Here, I_{D0} is designed equal to $75\mu\text{A}$. The opamp gets disabled upon unavailability of UPB, to help with the longevity of the energy stored on C_{stor} .

III. MEASUREMENT RESULTS

Fig. 5 illustrates the die photo of the purposed system. The whole die including pads measures $400\mu\text{m} \times 400\mu\text{m}$ where the active area is $110\mu\text{m} \times 145\mu\text{m}$. Fig. 6 Shows the schematic and a photo of the experimental setup for transient measurements.




Fig. 7: Transient measurement results.




Fig. 8: a) Rectified voltage and DC current load. b) Dust efficiency and equivalent DC resistive load. c) Startup time all over the acoustic intensity at the piezoelectric receiver.

A 2.55-ms burst signal with a carrier frequency of 2.79 MHz and including a series of notches with consequent durations of $20\mu\text{s}$, $25\mu\text{s}$, $33\mu\text{s}$, $43\mu\text{s}$, $53\mu\text{s}$, $62\mu\text{s}$, $72\mu\text{s}$, and $4\mu\text{s}$ is fed to an arbitrary signal generator. The generated signal is amplified by a 50 dB power amplifier and transmitted as a UPB through a water tank and using a commercial transducer. In the first step, the UPB is measured and validated by positioning a hydrophone in front of the transducer and capturing the UPB by an oscilloscope. In the next step, the prototype system composed of a $500\mu\text{m} \times 500\mu\text{m} \times 500\mu\text{m}$ piezoelectric receiver, the fabricated electronic die, the μLEDs , and the storage capacitors is moved in front of the transducer (i.e. in the same position that the hydrophone was placed in the

TABLE I: Summary of Specifications and Comparison.

	This Work	TBioCAS 2019 [7]	TBioCAS 2020 [8]	CICC 2018 [6]
Application	Dual-wavelength Optogenetics	Optogenetics	Optogenetics	Electrical stim.
Fully Programmable	Yes	No	No	Yes
Load Regulation	Yes	No	No	No
Technology	0.18 μm	0.18 μm	0.18 μm	65 nm LPCMOS
Chip Area/Active Area	0.17/0.016 mm ²	0.09/0.0075 mm ²	0.09/0.003 mm ²	1/0.06 mm ²
off-chip capacitors	100 nF	10 nF	10 nF	4 μF
Piezo/Dust volume	0.125/0.572* mm ³	0.153 mm ³ /N/A	0.125/2.85 mm ³	0.281/6.5 mm ³
Carrier Frequency	1-5 MHz	1-7 MHz	1.38 MHz	1.85 MHz
Output power range	0.4-3 mW	2.28 mW	0-6 mW	3 mW
Max. VCR	94.5 %	93.57 %	90.4 %	N/A
Max. Chip efficiency	92.5 % @ 2.6 mW	94.51 % @ 2.28 mW	91.2 % @ 2.4 mW	82% @ 120* μW
Overvoltage protection	Yes	No	No	N/A

* estimated




Fig. 9: The integration plan for the dust-sized system.

previous step). Then V_{REC} , I_{LED1} , and I_{LED2} are measured at the die's output using a handheld oscilloscope at three of its isolated channels. The currents are obtained by measuring voltage over 50Ω series test resistors (R_{t1} and R_{t2}). Fig. 7 presents the measured transient results at the output of the chip. As it is depicted in this figure, I_{LED2} increases from $0 - 514\mu\text{A}$ with steps of $74\mu\text{A} \pm 5\%$, V_{REC} is regulated to 2.8 V and $I_{Total} = I_{LED1} + I_{LED2}$ is regulated to $600\mu\text{A}$. In another measurement, the ultrasonic intensity of 2.5-ms continuous bursts is swept from $7.2\text{-}36\text{mW}/\text{mm}^2$ with steps of $1.8\text{mW}/\text{mm}^2$. Accordingly, V_{REC} , the DC current (i.e I_{LED1}), and startup times are measured. As illustrated in Fig. 8, the V_{REC} is measured $2.79\text{V} \pm 0.5\%$. However, as the acoustic intensity increases I_{LED1} increases and consequently the $R_{DC} = V_{REC}/I_{LED1}$ decreases. In the middle plot of Fig. 8, the dust efficiency (output electrical power divided by acoustic power at the piezo surface) and R_{DC} are depicted, highlighting the dependence of aperture efficiency to the electrical load. Finally, in the bottom plot, the startup time of the chip is shown that decreases by increasing the acoustic power. An integration plan with estimated volume of $0.572 (1.3 \times 0.80 \times 0.55)\text{mm}^3$, is shown in Fig.9. In order to comply with this plan, the chip PADs have been designed in a way that the custom-made μLEDs and the capacitor can be mounted on top of the chip using flip-chip bonding, and stud bumping techniques, respectively. For Dual μLED integration, first, the blue μLED is made on a sapphire substrate, then RED μLEDs are picked up from a releasable array and put beside the blue μLED using a transfer printer. Then, interconnects are made using the metal evaporation process. A summary of specifications and comparison table is presented in Table I.

IV. CONCLUSION

This letter proposes a load regulation scheme suppressing the need for adaptive matching and overvoltage protection circuits for multi-function ultrasonically powered devices. It is shown that for the application of a dual-wavelength optogenetic system, the proposed circuit divides the power/current budget between the two μLEDs in a power-efficient weighted manner. Furthermore, the longevity of the energy stored at C_{Stor} is boosted by driving the μLEDs only upon availability of UPB and disabling the unnecessary circuits in the absence of UPB. This way low-power circuits such as neural recording can be continuously powered by the stored energy at C_{Stor} .

REFERENCES

- [1] D. Seo *et al.*, "Wireless recording in the peripheral nervous system with ultrasonic neural dust," *Neuron*, vol. 91, no. 3, pp. 529–539, 2016.
- [2] M. M. Ghanbari *et al.*, "A sub-mm³ ultrasonic free-floating implant for multi-mote neural recording," *IEEE Journal of Solid-State Circuits*, vol. 54, no. 11, pp. 3017–3030, 2019.
- [3] M. Zamani *et al.*, "A 2.3- μW capacitively coupled chopper-stabilized neural amplifier with input impedance of 6.7 G Ω ," *IEEE Solid-State Circuits Letters*, vol. 4, pp. 133 – 136, 2021.
- [4] C. Shi *et al.*, "A 0.065-mm³ monolithically-integrated ultrasonic wireless sensing mote for real-time physiological temperature monitoring," *IEEE Transactions on Biomedical Circuits and Systems*, 2020.
- [5] M. J. Weber *et al.*, "A miniaturized single-transducer implantable pressure sensor with time-multiplexed ultrasonic data and power links," *IEEE Journal of Solid-State Circuits*, vol. 53, no. 4, pp. 1089–1101, April 2018.
- [6] B. C. Johnson *et al.*, "Stimdust: A 6.5mm³, wireless ultrasonic peripheral nerve stimulator with 82% peak chip efficiency," in *2018 IEEE Custom Integrated Circuits Conference (CICC)*. IEEE, 2018, pp. 1–4.
- [7] A. Rashidi *et al.*, "An implantable ultrasonically powered system for optogenetic stimulation with power-efficient active rectifier and charge-reuse capability," *IEEE Transactions on Biomedical Circuits and Systems*, vol. 13, no. 6, pp. 1362–1371, 2019.
- [8] K. Laursen *et al.*, "Ultrasonically powered compact implantable dust for optogenetics," *IEEE Transactions on Biomedical Circuits and Systems*, vol. 14, no. 3, pp. 583–594, 2020.
- [9] T. C. Chang *et al.*, "Design of tunable ultrasonic receivers for efficient powering of implantable medical devices with reconfigurable power loads," *IEEE Transactions on Ultrasonics, Ferroelectrics, and Frequency Control*, vol. 63, no. 10, pp. 1554–1562, Oct 2016.
- [10] A. Rashidi *et al.*, "Overvoltage protection circuits for ultrasonically powered implantable microsystems," in *2019 41st Annual International Conference of the IEEE Engineering in Medicine and Biology Society (EMBC)*, 2019, pp. 4354–4358.
- [11] J. Vierock *et al.*, "Bipoles is an optogenetic tool developed for bidirectional dual-color control of neurons," *Nature Communications*, vol. 12, no. 1, p. 4527, Jul 2021. [Online]. Available: <https://doi.org/10.1038/s41467-021-24759-5>