CORA Cork Open Research Archive
Cartlann Taighde Oscailte Chorcaí

Title	Inference in the spatial autoregressive efficiency model with an application to Dutch dairy farms
Authors	Skevas, Ioannis
Publication date	2019-10-28
Original Citation	Skevas, I. (2019) 'Inference in the spatial autoregressive efficiency model with an application to Dutch dairy farms', European Journal of Operational Research, 283(1), pp.356-364. https://doi.org/10.1016/j.ejor.2019.10.033
Type of publication	Article (peer-reviewed)
Link to publisher's version	http://www.sciencedirect.com/science/article/pii/S0377221719308689 - 10.1016/j.ejor.2019.10.033
Rights	© 2019 The Author. Published by Elsevier B.V. This is an open access article under the CC BY license. (http://creativecommons.org/licenses/by/4.0/) - http://creativecommons.org/licenses/by/4.0/
Download date	2026-11-15 02:26:52
Item downloaded from	https://hdl.handle.net/10468/9284

UCC
University College Cork, Ireland
Coláiste na hOllscoile Corcaigh

TECHNICAL APPENDIX

Inference in the spatial autoregressive efficiency model with an application to Dutch dairy farms

(Corresponding) Author: Ioannis Skevas, Lecturer, Department of Food Business and Development, University College Cork, O'Rahilly Building, College Rd, T12 K8AF, Cork, Ireland, Tel: +353 21 4902750, email: ioannis.skevas@ucc.ie

1 Spatial autoregressive efficiency model

1.1 Setup

Consider the model:

$$\mathbf{y}_t = \mathbf{a} + \mathbf{X}_t\boldsymbol{\beta} + \mathbf{v}_t + \log(\mathbf{TE}_t) \tag{1}$$

$$\mathbf{s}_t = \rho\mathbf{W}\mathbf{s}_{t-1} + \mathbf{Z}\boldsymbol{\delta} + \boldsymbol{\xi}_t \tag{2}$$

$$\mathbf{s}_0 = (\mathbf{I} - \rho\mathbf{W})^{-1}\mathbf{Z}\boldsymbol{\delta} + (\mathbf{I} - \rho\mathbf{W})^{-1}\boldsymbol{\xi}_0 \tag{3}$$

where $\mathbf{s}_t = \log\left(\frac{\mathbf{TE}_t}{1-\mathbf{TE}_t}\right)$. This relationship implies that $\mathbf{TE}_t = \frac{e^{\mathbf{s}_t}}{1+e^{\mathbf{s}_t}}$ and $\log(\mathbf{TE}_t) = \mathbf{s}_t - \log(1 + e^{\mathbf{s}_t})$. The following assumptions are made for the model's error components:

- $\mathbf{v}_t \sim \mathcal{N}(0, \tau\mathbf{I})$
- $\mathbf{a} \sim \mathcal{N}(0, \omega\mathbf{I})$
- $\boldsymbol{\xi}_t \sim \mathcal{N}(0, \phi\mathbf{I})$
- $\boldsymbol{\xi}_0 \sim \mathcal{N}(0, \phi(\mathbf{I} - \rho\mathbf{W})^2)$

where τ, ω and ϕ are precision parameters, while $\mathbf{I}$ is a $N \times N$ identity matrix[1].

Let $\boldsymbol{\theta} = [\omega, \boldsymbol{\beta}, \tau, \rho, \boldsymbol{\delta}, \phi]'$. Based on this setup, the complete-data likelihood is written as:

$$\begin{aligned} p(\mathbf{y}_t, \{\mathbf{a}\}, \{\mathbf{s}_t\}|\boldsymbol{\theta}, \mathbf{X}_t, \mathbf{Z}) &= p(\mathbf{y}_t|\{\mathbf{a}\}, \{\mathbf{s}_t\}, \boldsymbol{\beta}, \tau, \mathbf{X}_t) \times p(\{\mathbf{s}_t\}|\rho, \boldsymbol{\delta}, \phi, \mathbf{Z}) \times p(\{\mathbf{a}\}|\omega) \\ &= \frac{\tau^{NT/2}}{(2\pi)^{NT/2}} \exp\left\{ -\frac{\tau}{2}\sum_{t=0}^{T-1}[\mathbf{y}_t - \mathbf{a} - \mathbf{X}_t\boldsymbol{\beta} - \log(\mathbf{TE}_t)]^2 \right\} \\ &\times \frac{\boldsymbol{\phi}_0^{N/2}}{(2\pi)^{N/2}} \exp\left\{ -\frac{\boldsymbol{\phi}_0}{2}[\mathbf{s}_0 - (\mathbf{I} - \rho\mathbf{W})^{-1}\mathbf{Z}\boldsymbol{\delta}]^2 \right\} \\ &\times \frac{\phi^{N(T-1)/2}}{(2\pi)^{N(T-1)/2}} \exp\left\{ -\frac{\phi}{2}\sum_{t=1}^{T-1}(\mathbf{s}_t - \rho\mathbf{W}\mathbf{s}_{t-1} - \mathbf{Z}\boldsymbol{\delta})^2 \right\} \\ &\times \frac{\omega^{N/2}}{(2\pi)^{\frac{N}{2}}} \exp\left\{ -\frac{\omega}{2}\mathbf{a}^2 \right\} \end{aligned} \tag{4}$$

where $\boldsymbol{\phi}_0 = \phi(\mathbf{I} - \rho\mathbf{W})^2$.

[1]Note that in contrast to the manuscript where the second moment of the Normal distribution is parameterized in terms of variance (as this is more familiar to the audience), the current technical appendix uses the precision parameterization because it is customary in Bayesian analysis to work with precisions instead of variances. In practical terms, the precision is simply the inverse of the variance. Specifically, $\tau = \frac{1}{\sigma_v^2}$, $\omega = \frac{1}{\sigma_\alpha^2}$ and $\phi = \frac{1}{\sigma_\xi^2}$.

1.2 Priors

The following priors are imposed on the model's parameters:

- $p(\boldsymbol{\beta}) = \frac{|\mathbf{P}|^{1/2}}{(2\pi)^{K/2}} \exp\Big\{ -\frac{1}{2}(\boldsymbol{\beta}-\mathbf{m})'\mathbf{P}(\boldsymbol{\beta}-\mathbf{m})\Big\}$
- $p(\boldsymbol{\delta}) = \frac{|\mathbf{R}|^{1/2}}{(2\pi)^{L/2}} \exp\Big\{ -\frac{1}{2}(\boldsymbol{\delta}-\mathbf{q})'\mathbf{R}(\boldsymbol{\delta}-\mathbf{q})\Big\}$
- $p(\tau) = \frac{b_\tau^{a_\tau}}{\Gamma(a_\tau)}\tau^{a_\tau-1}e^{-b_\tau\tau}$
- $p(\omega) = \frac{b_\omega^{a_\omega}}{\Gamma(a_\omega)}\omega^{a_\omega-1}e^{-b_\omega\omega}$
- $p(\phi) = \frac{b_\phi^{a_\phi}}{\Gamma(a_\phi)}\phi^{a_\phi-1}e^{-b_\phi\phi}$
- $p(\rho) = \frac{\rho^{a-1}(1-\rho)^{b-1}}{B(a,b)}$

1.3 Posterior

The posterior density of the model's parameters and the latent data is:

$$\pi(\boldsymbol{\theta}, \{\mathbf{a}\}, \{\mathbf{s}_t\}|\mathbf{y}_t, \mathbf{X}_t, \mathbf{Z}) \propto p(\mathbf{y}_t, \{\mathbf{a}\}, \{\mathbf{s}_t\}|\boldsymbol{\theta}, \mathbf{X}_t, \mathbf{Z}) \times p(\boldsymbol{\theta}) \tag{5}$$

where $p(\mathbf{y}_t, \{\mathbf{a}\}, \{\mathbf{s}_t\}|\boldsymbol{\theta}, \mathbf{X}_t, \mathbf{Z})$ is the complete-data likelihood defined in subsection 1.1 and $p(\boldsymbol{\theta})$ is the product of all prior densities defined in subsection 1.2.

1.4 Full conditionals

For convenience, the following are defined: $\mathbf{y}_t^* = \mathbf{y}_t - \mathbf{a} - \log(\mathbf{TE}_t)$, $\mathbf{s}_t^* = \mathbf{s}_t - \rho\mathbf{W}\mathbf{s}_{t-1}$, $\mathbf{d}_t^* = \mathbf{s}_t - \mathbf{Z}\boldsymbol{\delta}$, $\mathbf{g}_t^* = \mathbf{y}_t - \mathbf{a} - \mathbf{X}_t\boldsymbol{\beta}$.

The full conditionals of the structural parameters and the latent states are:

- The full conditional for $\boldsymbol{\beta}$ is a multivariate Normal:

$$\pi(\boldsymbol{\beta}|\cdot) = \frac{|\tilde{\mathbf{P}}|^{1/2}}{(2\pi)^{K/2}} \exp\Big\{ -\frac{1}{2}(\boldsymbol{\beta}-\tilde{\mathbf{m}})'\tilde{\mathbf{P}}(\boldsymbol{\beta}-\tilde{\mathbf{m}})\Big\}$$

  where:

  - $\tilde{\mathbf{m}} = (\tau\mathbf{X}_t'\mathbf{X}_t + \mathbf{P})^{-1}(\tau\mathbf{X}_t'\mathbf{y}_t^* + \mathbf{P}\mathbf{m})$
  - $\tilde{\mathbf{P}} = \tau\mathbf{X}_t'\mathbf{X}_t + \mathbf{P}$

- The full conditional for $\boldsymbol{\delta}$ is a multivariate Normal:

$$\pi(\boldsymbol{\delta}|\cdot) = \frac{|\tilde{\mathbf{R}}|^{1/2}}{(2\pi)^{L/2}} \exp\Big\{ -\frac{1}{2}(\boldsymbol{\delta}-\tilde{\mathbf{q}})'\tilde{\mathbf{R}}(\boldsymbol{\delta}-\tilde{\mathbf{q}})\Big\}$$

  where:

  - $\tilde{\mathbf{q}} = (\phi\mathbf{Z}'\mathbf{Z} + \mathbf{R})^{-1}(\phi\mathbf{Z}'\mathbf{s}_t^* + \mathbf{R}\mathbf{q})$
  - $\tilde{\mathbf{R}} = \phi\mathbf{Z}'\mathbf{Z} + \mathbf{R}$

- The full conditional for τ is a Gamma:

$$\pi(\tau|\cdot) = \frac{\tilde{b}_{\tau}^{\tilde{a}_{\tau}}}{\Gamma(\tilde{a}_{\tau})}\tau^{\tilde{a}_{\tau}-1}e^{-\tilde{b}_{\tau}\tau}$$

  where:

  - $\tilde{a}_{\tau} = \frac{NT}{2} + a_{\tau}$
  - $\tilde{b}_{\tau} = \frac{1}{2}(\mathbf{y}_t^* - \mathbf{X}_t\boldsymbol{\beta})'(\mathbf{y}_t^* - \mathbf{X}_t\boldsymbol{\beta}) + b_{\tau}$

- The full conditional for ω is a Gamma:

$$\pi(\omega|\cdot) = \frac{\tilde{b}_{\omega}^{\tilde{a}_{\omega}}}{\Gamma(\tilde{a}_{\omega})}\omega^{\tilde{a}_{\omega}-1}e^{-\tilde{b}_{\omega}\omega}$$

  where:

  - $\tilde{a}_{\omega} = \frac{N}{2} + a_{\omega}$
  - $\tilde{b}_{\omega} = \frac{1}{2}\mathbf{a}^2 + b_{\omega}$

- The full conditional for ϕ is a Gamma:

$$\pi(\phi|\cdot) = \frac{\tilde{b}_{\phi}^{\tilde{a}_{\phi}}}{\Gamma(\tilde{a}_{\phi})}\phi^{\tilde{a}_{\phi}-1}e^{-\tilde{b}_{\phi}\phi}$$

  where:

  - $\tilde{a}_{\phi} = \frac{NT}{2} + a_{\phi}$
  - $\tilde{b}_{\phi} = \frac{(\mathbf{I}-\rho\mathbf{W})^2}{2}[\mathbf{s}_0 - (\mathbf{I}-\rho\mathbf{W})^{-1}\mathbf{Z}\boldsymbol{\delta}]^2 + \frac{1}{2}(\mathbf{s}_t - \rho\mathbf{W}\mathbf{s}_{t-1} - \mathbf{Z}\boldsymbol{\delta})^2 + b_{\phi}$

- The full conditional for ρ does not belong to any known family:

$$\begin{aligned}\pi(\rho|\cdot) = \exp\left\{ -\frac{\boldsymbol{\phi}_0}{2}\Big[[(\mathbf{I}-\rho\mathbf{W})^{-1}\mathbf{Z}\boldsymbol{\delta}]^2 - 2\mathbf{s}_0(\mathbf{I}-\rho\mathbf{W})^{-1}\mathbf{Z}\boldsymbol{\delta}\Big]\right\} \\ \times \exp\left\{ -\frac{\phi}{2}\sum_{t=1}^{T-1}\Big[(\rho\mathbf{W}\mathbf{s}_{t-1})^2 - 2\mathbf{d}_t^*\rho\mathbf{W}\mathbf{s}_{t-1}\Big]\right\} \\ \times \rho^{a-1}(1-\rho)^{b-1}\end{aligned}$$

- The full conditional for $\mathbf{a}$ is Normal:

$$\pi(\mathbf{a}|\cdot) = \frac{\tilde{t}^{N/2}}{(2\pi)^{N/2}}\exp\left\{ -\frac{\tilde{t}}{2}(\mathbf{a}-\tilde{\mathbf{c}})\right\}$$

  where:

  - $\tilde{\mathbf{c}} = \frac{\tau}{\tilde{\mathbf{t}}}\sum_{t=1}^{T}[\mathbf{y}_t - \mathbf{X}_t\boldsymbol{\beta} - \log(\mathbf{T}\mathbf{E}_t)]$
  - $\tilde{t} = \tau T + \omega$

- The full conditional for $\mathbf{s}_0$ does not belong to any known family:

$$\begin{aligned}\pi(\mathbf{s}_0|\cdot) = \exp\left\{ -\frac{\tau}{2}\Big[[\mathbf{s}_0 - \log(1+e^{s_0})]^2 - 2\mathbf{g}_0^*[\mathbf{s}_0 - \log(1+e^{s_0})]\Big]\right\} \\ \times \exp\left\{ -\frac{1}{2}\left[\mathbf{s}_0^2(\boldsymbol{\phi}_0 + \phi\rho^2\mathbf{W}^2) - 2\mathbf{s}_0\Big[(\mathbf{I}-\rho\mathbf{W})^{-1}\mathbf{Z}\boldsymbol{\delta}\boldsymbol{\phi}_0 + \phi\rho\mathbf{W}(\mathbf{s}_1 - \mathbf{Z}\boldsymbol{\delta})\Big]\right]\right\}\end{aligned}$$

- The full conditional for $\mathbf{s}_t$ does not belong to any known family:

$$\pi(\mathbf{s}_t|\cdot) = \exp\left\{ -\frac{\tau}{2}\sum_{t=0}^{T-1}\Big[[\mathbf{s}_t - \log(1+e^{s_t})]^2 - 2\mathbf{g}_t^*[\mathbf{s}_t - \log(1+e^{s_t})]\Big]\right\}$$
$$\times \exp\left\{ -\frac{\phi}{2}\sum_{t=1}^{T-1}\left[\mathbf{s}_t^2(\mathbf{I}+\rho^2\mathbf{W}^2) - 2\mathbf{s}_t\Big[(\mathbf{I}-\rho\mathbf{W})\mathbf{Z}\boldsymbol{\delta} + \rho\mathbf{W}(\mathbf{s}_{t+1}+\mathbf{s}_{t-1})\Big]\right]\right\}$$

- The full conditional for $\mathbf{s}_{t-1}$ does not belong to any known family:

$$\pi(\mathbf{s}_{t-1}|\cdot) = \exp\left\{ -\frac{\tau}{2}\sum_{t=1}^{T-1}\Big[[\mathbf{s}_{t-1} - \log(1+e^{s_{t-1}})]^2 - 2\mathbf{g}_t^*[\mathbf{s}_{t-1} - \log(1+e^{s_{t-1}})]\Big]\right\}$$
$$\times \exp\left\{ -\frac{\phi}{2}\sum_{t=2}^{T-1}\left[\mathbf{s}_{t-1}^2 - 2\mathbf{s}_{t-1}[\mathbf{Z}\boldsymbol{\delta} + (\mathbf{I}-\rho\mathbf{W})\mathbf{s}_{t-2}]\right]\right\}$$